



Full HD
(1920x1080 25 fps)

IP Camera Line 2MP Dome

Installation instructions


Package contents

IP camera	1 pc.
Plastic, detachable, sealed Ethernet cable connector with rubber seals in an individual transparent package	1 pc.
Metal screws with plastic wall plugs for securing the body to a surface, a service hex key in an individual transparent package.	
Quantity:	
screws	3 pcs.
wall plugs	3 pcs.
key	1 pc.
Silica gel packet (inside the casing)	1 pc.
Instructions	1 pc.
Sticker — assembly template	1 pc.


Specifications

Video	2 MP (1st stream 1920x1080, 2nd stream 640x360), up to 25 fps, H.264, H.265 compression, bit rate up to 6 Mbps
Audio	built-in microphone, MP3 compression, bit rate 64 Kbps
Recording	to network storage, cloud server, SD card, Line server
Supported SD cards	microSDXC up to 512 GB, recommended file system Ext4
Network protocols	TCP/IP, UDP, HTTP, DHCP, DNS, DDNS, IPV4, NTP, RTSP, SMTP, SMB, ONVIF
Design	bullet (cylinder), for indoor and outdoor use
Matrix	SC2235, 1/2.7 inches
Lens	Model IPC10P2MOBI10F28 - fixed / f=2.8 mm, field of view 102; model IPC10P2MOBI10F36 - fixed / f=3.6 mm, field of view 88
Infrared illumination	Yes, up to 30 m
Network interface	Ethernet port, 10Base-T / 100Base-TX
Power	12 V, 0.5 A, 5.5 mm DC jack (PoE IEEE 802.3af)
IP protection class / operating temperature	IP65/-20~ 50 °C with humidity 90% or less (non-condensing)
Dimensions / net weight	97x114x114 (mm) / 460 grams

Connection diagram



Input connectors



Installation

- /1** To record to an SD card, remove the protective cover from the camera body and insert the SD card into the slot. Close the cover and tighten the screws.
- /2** Mount the camera on a surface using the parts provided. Do not fully tighten the mountings, as you will need to manually adjust the camera position after connecting and displaying video in the client side.
- /3** Connect the power supply to the 12 V connector or UTP cable to network equipment that supports PoE.

Operating instructions



- ▶ Do not use the camera near any potential source of magnetic, electromagnetic radiation, thermal energy, or allow exposure to active chemicals, laser radiation, steam, smoke or an open flame. Ensure natural ventilation.
- ▶ When wiring the power, you must ensure earthing and lightning protection is provided and, if possible, use an uninterruptible power supply. Make sure that the power supply is working correctly; do not supply signals to device inputs that do not comply with the purpose and limitations of these inputs.
- ▶ Ensure that the power is disconnected during installation and maintenance (washing, replacing the SD card, adjustment).
- ▶ Do not throw the camera or expose it to impacts. Do not aim the camera lens at a bright light source (the sun or incandescent lamp). Do not immerse the camera in water or any other liquid.
- ▶ When installing the camera outdoors, use the Ethernet connector that is included in the package, as well as a junction box (sealed box) with at least IP54 protection.
- ▶ If the item is not working as it should, contact the manufacturer. Do not try to disassemble or repair the camera yourself. The manufacturer shall not be liable for any problems caused by unauthorized repairs or maintenance.

Setting up

- /1** Download the client application for your operating system from <https://devline.net/> or <https://myvms.app/>.
- /2** Make sure that the application and camera are on the same network.
- /3** Launch the application. In Network Connections, go to the Admintool tab, select a device from the list, and set it up or connect to use.
- /4** By default, the camera does not have a static IP address and waits to automatically obtain the IP via DHCP. We recommend setting up a static IP address in Admintool. Before assigning an IP address, make sure that this address is not taken by another device in the local network, otherwise an IP address conflict will arise.
- /5** When connecting, use the log in details from the sticker that is provided with the camera.

More information can be found at <https://devline.net/ipcam>

You can download more information on using the client application from <https://devline.net/>.



Important! The manufacturer reserves the right to upgrade the design, technical specifications, appearance and the product's contents without prior notice.

DOME